Included

Remote control 2.1
One push of the button is enough to select the radio or an additional sound source you've connected, to control the volume, and then operate the radio. You can also save the radio pre-sets to the memory function.

RM2.1

Optional

Wireless 8-way wall transmitter
This offers you nearly the same possibilities as the unit described adjacent. The wall transmitter consists of a base (410-00003) and is available in three standard colours.

white
120-76100 - cover
120-00050-11 keys

grey
121-76100 - cover
121-00050-11 keys

anthracite
122-76100 - cover
122-00050-11 keys

410-00003 (basic unit)

ART2.1

Never before was it so easy to provide music in an extra room. The extremely compact and thus discreet housing of the ART2.1 contains a stereo amplifier, an FM tuner with four pre-sets and the option of connecting it to an external sound source. Thanks to its minimal dimensions, you can easily hide the device in a false ceiling, for example, via the hole for the inwall loudspeakers. The advantage of the RF remote control included is that you don't have to stay within the ART2.1's 'line of sight'. This allows you to easily choose your favourite music and control the volume, wherever you happen to be.

description	local audio distribution system Class D 2 x 6W RMS (4 Ohm)
sources	1 x built-in FM tuner (external antenna / 4 pre-sets) 1 x AUX input (mini stereo jack)
operation	built-in RF receiver 868 MHZ (Easywave) RF remote control (10 buttons) = wall bracket optional 8-way RF wall control possible
various features	volume control, 4 FM pre-sets, AUX input compact housing mono-stereo switch power supply 110 V - 230 V
weight	0.5 kg
dim. mm (h x w x d)	120 x 65 x 40

artsound

ArtSound • Kazerneweg 15 • B-9770 Kruishoutem
tel. + 32-(0)9 380 81 80 • + 32-(0)9 386 12 35
www.jobetrade.be • info@artsound.be • info@artsound.nl